



# Alarm.com Smart Chime Data Sheet

ADC-W115C-INT

[www.alarm.com](http://www.alarm.com)

© 2021 Alarm.com. All rights reserved. 210913

## Specifications

**Wi-Fi Connection:** 802.11 b/g/n, 2.4 GHz

**Wi-Fi Security:** WPA2

**Power:** 12 VDC Power adapter with interchangeable plugs (included)

**LED Indicators:** 4

**Buttons:** WPS, Reset

**Antennas:** 2 Wi-Fi

**Chime:** 1.5 W speaker, 77 dB

**Operating Temperature:** 32°F to 104°F (0°C to 40°C)

**Operating Humidity:** 10% to 90% (non-condensing) RH

**Dimensions (H x W x D):** With antennas 12.27 x 13.0 x 5.7cm (5.0 x 5.1 x 2.25")

Without antennas 8.5 x 8.5 x 5.7 cm (3.3 x 3.3 x 2.25")



## Overview

Designed to work seamlessly with the Alarm.com platform, the ADC-W115C-INT serves as a robust Wi-Fi extender and customizable wireless doorbell chime. Add the Alarm.com Smart Chime to an account when an in-home chime is not a feasible option during a doorbell camera installation. Simply pair the ADC-W115C-INT with the existing router, add to an account, add a doorbell camera, and enjoy boosted network signals that provide instantaneous chime notifications.

## Features

- Wireless doorbell chime
- Wi-Fi extender (2.4 GHz)
- Adjustable chime volume
- Customizable tones
- Remote management and troubleshooting

## In the Box

- ADC-W115C-INT Alarm.com Smart Chime
- Installation guide
- Power adapter
- Interchangeable plugs
- Mounting hardware
- Rubber feet

## LED Guide

🔌	☁️	📶	🔄	🔌☁️📶🔄
<b>On</b> <i>Device powered on</i>	<b>On</b> <i>Connected to Internet</i>	<b>On</b> <i>Device connected to chime</i>	<b>Off</b> <i>WPS mode not enabled</i>	<b>Blinking (escalating)</b> <i>Firmware upgrade in progress</i>
<b>Off</b> <i>Device powered off</i>	<b>Off</b> <i>No local or Internet connection</i>	<b>Off</b> <i>No device connected to chime</i>	<b>Blinking (slowly)</b> <i>WPS mode enabled to connect to router</i>	<b>Blinking (simultaneously)</b> <i>Reset in progress</i>
<b>Blinking</b> <i>Device booting up</i>	<b>Blinking</b> <i>Local connection, no Internet connection</i>	<b>Blinking (3 quick blinks)</b> <i>New device connected to chime</i>	<b>Blinking (rapidly)</b> <i>WPS mode enabled to connect to device</i>	
	<b>Blinking (5 quick blinks)</b> <i>Communication test initiated</i>			