
Stream Video Recorder (ADC-SVR122) - Data Sheet

Designed specifically to work with the Alarm.com hosted video service, the ADC-SVR122 Stream Video Recorder provides a 24x7 professional local video storage solution. With the Stream Video Recorder, you can connect up to eight Alarm.com video cameras for continuous recording.

Included Accessories

- Stream Video Recorder (SVR)
- Power Adapter
- Quick Installation Guide



Specifications

Recording channels

Up to 8 Cameras



Compatible cameras

- ADC-V520
- ADC-V520IR
- ADC-V521IR
- ADC-V522IR
- ADC-V620PT
- ADC-V720
- ADC-V720W
- ADC-V721W
- ADC-V722W
- ADC-V820
- ADC-V821
- ADC-VC725
- ADC-VC726
- ADC-VC825
- ADC-VC826
- ADC-VS120
- ADC-VS121
- ADC-VS420

Transcoded playback

MPEG4 H.264

Seed control

1x, 4x, 8x, 16x

HDD bay

1 Bay, 500GB or 1TB

Ethernet connection

10Base-T/100BaseTX (RJ45)

HDMI and USB connections

Locally view live and recorded video

Cooling

Fanless Thermal Heat Sink

Dimensions

3.5 x 3.5 x 5.8" (88 x 88 x 146.7 mm)

Operating temperature

32°-104°F (0°-40°C)

Storage temperature

-13° to 158°F (-25° to 70°C)

Operating humidity

20%-95% RH (non-condensing)

Power adaptor

12V DC 1.5A with UL/CE/FCC certification

LED GUIDE



LED location

LED status

Description

STATUS LED

Front of SVR



Solid Green

Local network and Internet connection

Flashing Green

Local connection only, no Internet

Flashing Red (1 sec)

No connection

Solid Red

Error check LEDs on back

Flashing Green & Red

Factory Reset

SVR HARD DRIVE

Back of SVR



Solid Green

SVR hard drive is operating normally

Flashing Green

Hard drive is full. Oldest footage is being deleted

Flashing Red

Hard drive configuration error

CAMERAS 1-8

Back of SVR



Solid Green

Camera is connected and recording

Flashing Green

Camera connected and recording paused

Flashing Red

Camera disconnected

